

HIGH-FREQUENCY CIRCUIT DEVICE

5

BACKGROUND OF THE INVENTION

Field of the Invention

The present invention relates to a high-frequency circuit device, and particularly to a high-frequency circuit device suitable for use in a terminal device for mobile communications.

10 Description of the related Art

Fig. 13 is a plan view of a conventional high output amplifier. Fig. 14 is a circuit diagram showing an equivalent circuit of the high output amplifier.

In Fig. 13, reference numeral 100 indicates a high output amplifier, reference numeral 102 indicates a semiconductor substrate, reference numerals 104 indicate transistors, reference numerals 106 indicate microstrip lines each having a $\lambda/4$ electrical length, which are respectively impedance converter circuits, reference numeral 108 indicates a signal terminal, reference numeral 110 indicates a signal output terminal, and reference numerals 112 indicate via holes, respectively. A chip size of the high output amplifier 100 is normally a square of 1mm to several tens of mm in most cases. A ground conductor is formed on the back or reverse side of the semiconductor substrate 102. The thickness of the semiconductor substrate ranges from about 30 μ m to about 150 μ m.

The transistors 104 used as basic elements of the high output amplifier 100 are commonly very low in input/output impedance (25 Ω or less). In addition to it, a plurality of transistors are normally arranged in parallel to increase an output voltage. Therefore, the impedance is further lowered.

On the other hand, since the characteristic impedance of an

external circuit is set to 50Ω as a standard, it is necessary to provide means for matching the impedances of the two to each other. One used for its purpose is a method of using a microstrip line having a $\lambda/4$ electrical length as an impedance converter circuit.

5 When the input impedances of each single transistors 104 are supposed to be 10Ω as shown in Fig. 14, they are respectively converted to 50Ω by $\lambda/4$ electrical-length microstrip lines adjacent to the transistors 104, which in turn are combined into one. Thus, a method is adopted in which since the resultant
10 characteristic impedance results in a half 25Ω , it is converted to 50Ω by a $\lambda/4$ electrical-length microstrip line adjacent to the signal input terminal 108, whereby matching with the external circuit is made. This method is commonly used in a high output amplifier because a design error is small and capacitors and
15 inductors are unnecessary.

However, the method using the $\lambda/4$ electrical-length microstrip lines as the impedance converter circuits has the following problems.

20 Firstly, the configuration shown in Fig. 13 is easy to form such an unwanted or unnecessary oscillation loop as shown in Fig. 14 and produce oscillations. The isolation (backward transfer characteristic) of each transistor may be set larger than forward gain to make it hard to produce the unwanted oscillation loop. However, the isolation of the transistor is commonly deteriorated
25 as the frequency increases. It is thus difficult to ensure it. Assuming that the operating frequency is 5GHz, for example, the gain of a high output transistor at 5GHz ranges from 15dB to 25dB, whereas the isolation thereof ranges from -20dB ~ -30dB. It cannot be said that the difference between the two is sufficient.

30 Further, in the configuration shown in Fig. 13, an input-side matching circuit and an output-side matching circuit respectively need three-by-three $\lambda/4$ electrical-length microstrip

TOP SECRET

lines.

Assuming that the operating frequency is 5GHz and the shortening coefficient of a waveform on the semiconductor substrate 102 is $1/2.5$, the $\lambda/4$ electrical-length microstrip line needs a length of 6mm. When six $\lambda/4$ electrical-length microstrip lines are used, a chip size becomes a square of several tens of mm even at the minimum. This might cause an obstacle to a reduction in size and cost. When the microstrip line is used as for an information terminal for mobile communications in particular, a reduction in size and cost is a large item to be considered from the viewpoint of design in a portable or cellular telephone or the like in particular. There were often difficulties in satisfying its design requirements.

Incidentally, Japanese Patent Application Laid-Open No. Sho 64-1301 describes an MIC isolator but has not a description thereof used in a distribution/synthetic circuit.

Summary of the Invention

The present invention has been made to solve the above-described problems. Therefore, an object of the present invention is to obtain a high-frequency circuit device hard to produce unnecessary oscillations.

According to one aspect of the invention, there is provided a high-frequency circuit device comprising: a distribution circuit for distributing a signal inputted from a signal input terminal to a plurality of first lines through a branch portion; a synthetic circuit for combining signals inputted from a plurality of second lines into one through a combined portion as an output signal and outputting it from a signal output terminal; transistors respectively placed between one ends of each individual first lines of the distribution circuit and one ends of each individual second lines of the synthetic circuit; and isolators respectively

Accordingly, this inventive high-frequency circuit device makes it hard to form an unwanted oscillation loop. In its turn, a high-reliability high-frequency circuit device can be configured.

According to another aspect of the invention, there is provided a high-frequency circuit device comprising: a distribution circuit for distributing a signal inputted from a signal input terminal to a plurality of first lines respectively having a plurality of first impedance converter circuits through a branch portion; a synthetic circuit for combining signals inputted from a plurality of second lines each having a second impedance converter circuit into one through a combined portion as an output signal and outputting it from a signal output terminal; transistors respectively placed between one ends of each individual first lines of the distribution circuit and one ends of each individual second lines of the synthetic circuit; and isolators connected either between the transistors and the branch portion of the distribution circuit or between the transistors and the combined portion of the synthetic circuit.

Other objects and advantages of the invention will become apparent from the detailed description given hereinafter. It should be understood, however, that the detailed description and specific embodiments are given by way of illustration only since

5

Fig. 1 is a plan view showing a high output amplifier in accordance with one embodiment of the invention;

Fig. 2 is a circuit diagram illustrating an equivalent circuit of the high output amplifier shown in Fig. 1;

Fig. 4 is a typical diagram showing the flow of high-frequency signals in the circulator in accordance with one
15 embodiment of the invention;

Fig. 5 is a typical diagram illustrating the flow of high-frequency signals in an isolator in accordance with one embodiment of the invention;

Fig. 6 is a circuit diagram depicting an equivalent circuit
20 as viewed from a port 2 of the isolator in accordance with one
embodiment of the invention;

Fig. 7 is a plan view showing a high output amplifier in accordance with another embodiment of the invention;

Fig. 8 is a circuit diagram illustrating an equivalent
25 circuit of the high output amplifier shown in Fig. 7;

Fig. 9 is a plan view depicting a high output amplifier in accordance with further embodiment of the invention;

Fig. 10 is a circuit diagram showing an equivalent circuit of the high output amplifier shown in Fig. 9;

Fig. 11 is a typical diagram illustrating an internal configuration of a circulator in accordance with further embodiment of the invention;

Fig. 13 is a plan view illustrating a conventional high output amplifier; and

In all figures, the substantially same elements are given the same reference numbers.

Preferred embodiments of the present invention will hereinafter be described in detail with reference to the accompanying drawings.

The first embodiment is one wherein isolators kept constant in input/output impedance are respectively connected between microstrip lines having $\lambda/4$ electrical lengths, which are used as input impedance converter circuits, and transistors and between microstrip lines having $\lambda/4$ electrical lengths, which are used as output impedance converter circuits, and the transistors, and the isolators are enhanced in isolation.

Fig. 1 is a plan view of a high output amplifier according to the first embodiment. Fig. 2 is a circuit diagram showing an equivalent circuit of the high output amplifier shown in Fig. 1.

In Fig. 1, reference numeral 10 indicates the high output amplifier. The high output amplifier 10 constitutes an MMIC chip. Reference numeral 12 indicates a semiconductor substrate, which is comprised, for example, GaAs, InP, Si or the like. A chip size is a square of from 1mm to several tens of mm, and the thickness of the semiconductor substrate ranges from 30 μ m to 150 μ m. A ground conductor (not shown) such as Au is formed on the back or reverse

side of the semiconductor substrate 12. Reference numerals 14 indicate transistors placed on the semiconductor substrate 12. In the present embodiment, FETs are used as the transistors. Reference numeral 16 indicates a distribution circuit placed on the semiconductor substrate 12. Reference numeral 16a indicates a branch portion of the distribution circuit 16. Reference numerals 16b indicate a plurality of first lines which branch off from the branch portion 16a of the distribution circuit 16. In the present embodiment, the two branch off from the branch portion 16a. Reference numerals 16c indicate impedance converter circuits which constitute the first lines 16b respectively. They are, for example, low-impedance microstrip lines, i.e., microstrip lines each having a $\lambda/4$ electrical length.

Reference numeral 18 indicates a composite or synthetic circuit placed in the semiconductor substrate 12. Reference numeral 18a indicates a confluent or combined portion of the synthetic circuit 18. Reference numerals 18b indicate second lines constituting branch lines, which join the combined portion 18a of the synthetic circuit 18. Reference numerals 18c indicate impedance converter circuits which constitute the second lines 18b respectively. They are, for example, low-impedance microstrip lines, i.e., microstrip lines each having a $\lambda/4$ electrical length.

Reference numeral 20 indicates a signal input terminal for applying a signal to the distribution circuit 16. Reference numeral 22 indicates a signal output terminal for outputting a signal from the synthetic circuit 18.

Reference numerals 24 indicate isolators, reference numerals 26 indicate circulators which constitute the isolators 24 respectively. Reference numerals 28 indicate terminal resistors respectively. Reference numerals 30 indicate via holes which are connected from circuits on the surface of the semiconductor substrate 12 to the ground conductor formed on the back of the

semiconductor substrate 12.

Each of the isolators 24 has input and output ports connected between a gate used as a control electrode of the transistor 14 and the microstrip line 16c having the $\lambda/4$ electrical length on the signal input side of the transistor 14. Each of the isolators 24 has input and output ports connected between a drain electrode of the transistor 14 and the microstrip line 18c having the $\lambda/4$ electrical length on the signal output side of the transistor 14. The terminal resistors 28 are connected to their corresponding via holes 30.

Fig. 3 is a typical diagram showing an internal configuration of the circulator 26 which constitutes the isolator 24 according to the first embodiment. Fig. 4 is a typical diagram illustrating the flow of high-frequency signals in the circulator 26.

In Fig. 3, the circulator 26 comprises three ports which are portions for generally inputting and outputting signals, i.e., a first port 32, a second port 34 and a third port 36. Signal lines for the first port 32, second port 34 and third port 36 comprise microstrip lines respectively, which correspond to a signal line 38 (comprising 38a and 38b), a signal line 40 (comprising 40a and 40b) and a signal line 42 (comprising 42a and 42b) respectively.

Reference numerals 44, 46 and 48 indicate impedance matching capacitors respectively. Reference numeral 50 indicates a ferrite which constitutes a magnet for applying a magnetic field.

The respective one signal lines of the signal lines 38, 40 and 42 of the circulator 26 are grounded. In Fig. 4, for example, the signal line 38b, signal line 40b and signal line 42b are grounded.

In Fig. 4, a signal inputted to the first port 32 is outputted to the second port 34, a signal inputted to the second

14 is set as 10Ω as shown in Fig. 2, the input/output impedance of the isolator 24 is also matched with 10Ω in this case. Since the isolators are identical to each other in input/output impedance, impedance matching is carried out by microstrip lines 16c each
5 having a $\lambda/4$ electrical length.

Namely, the input/output impedances of the isolators 24 are respectively converted to 50Ω by the $\lambda/4$ electrical-length microstrip lines 16c for first lines 16b adjacent to the isolators 24. The resultant converted impedances are combined into one by
10 the two first lines 16b. Consequently, the resultant characteristic impedance is brought to a half 25Ω . Therefore, the resultant impedance 25Ω is converted to 50Ω by a $\lambda/4$ electrical-length microstrip line 16c provided between a branch portion 16a and a signal input terminal 20 to thereby make matching with an
15 external circuit.

Incidentally, the impedance after having been converted by the $\lambda/4$ electrical-length microstrip line 16c constituting the first line 16b adjacent to each isolator 24, may be an arbitrary value. In this case, however, the impedance of each transistor 14
20 is matched to 10Ω and the input/output impedance of each isolator 24 is also matched to 10Ω . Further, the first lines 16b adjacent to the isolators 24 are separated into two. Therefore, the impedance is from over 10Ω to under 100Ω .

A description has been made of the signal input side of
25 each transistor 14 in the present embodiment. While, however, the impedance is slightly increased on the signal output side, the impedances of the isolators 24 and their corresponding $\lambda/4$ electrical-length microstrip lines 18c are similarly set.

In the high output amplifier 10, the isolators identical in
30 input/output impedance are respectively connected between the $\lambda/4$ electrical-length microstrip lines 16c on the signal input side and their corresponding transistors 14 and between the $\lambda/4$

00003898-062904
F00290-888860

chip.

While the isolators having the values identical to each other in input impedance and output impedance are used in the first embodiment, isolators having values different from one another in input impedance and output impedance are used in the second embodiment.

Each of isolators 24 has signal input and output ports connected between a gate used as a control electrode of a transistor 14 and a first line 16b on the signal input side of the transistor 14. Each of the isolators 24 has signal input and output ports connected between a drain electrode of the transistor 14 and a second line 18b on the signal output side of the transistor 14. Terminal resistors 28 are connected to their corresponding via holes 30.

Assuming that the impedance of each transistor 14 is 10Ω , the impedance of the isolators 24 on the transistor 14 side is matched to the transistor 14 and set to 10Ω , and the impedance of the isolators 24 on the first port 32 side as viewed from the signal input side is set to 100Ω . When the impedances on the first port 32 side, each of which has been set to 100Ω , are combined into one by the two first lines 16b, the combined impedance results in a half 50Ω , whereby the matching with an external circuit is achieved.

Since the isolators 24 perform impedance matching in the high output amplifier 60, it is not necessary to additionally provide impedance matching circuits, e.g., $\lambda/4$ electrical-length microstrip lines. Further, a chip is angled so that a chip size ranges from about 4mm to about 5mm. The chip size can be reduced as compared with the provision of the impedance matching circuits. Therefore, the high output amplifier 60 can be reduced in size and an expensive semiconductor substrate can be rendered small and configured at a low price.

5

10

15

25

30

•

configuration is operated as a push-pull amplifier.

In the high output amplifier 62 as described above, the isolators 24 are respectively configured with both line ends of either ones of the respective input/output ports as the signal line ends at either ones of their input/output ports. The isolators 24 are placed at the branch portion 16a of the distribution circuit 16 and the combined portion 18a of the combination or synthetic circuit 18. The isolator 24 placed at the branch portion 16a is connected to the first lines 16b different from each other with both line ends 40a and 40b of the second port 34 corresponding to its output port as the signal line ends. The isolator 24 provided at the combined portion 18a is connected to the second lines 18b different from each other with both line ends 38a and 38b of the first port 32 corresponding to its input port as the signal line ends. Owing to such a configuration, the number of the isolators 24 may be two at the minimum. The required number of isolators 24 is reduced as compared with the second embodiment, and the area of the chip can be further reduced. In its turn, a high-reliability amplifier can be configured which is small in size and hard to form an unwanted oscillation loop.

In the description referred to above, the configuration using the FET as the transistors has been explained. However, even if the transistors are comprised of HBT or bipolar transistors, a similar effect is brought about.

The MMIC-configured amplifier has been illustrated as the high output amplifier by way of example. However, even if an MIC-configured amplifier using discrete transistors is adopted, a similar effect is obtained.

While the isolator configured using the microstrip line has been illustrated as an example, an isolator using a coaxial cable may be used. Further, the isolator may be one configured as a

chip. Alternatively, even if an isolator monolithically formed on an MMIC is adopted, a similar effect is brought about.

Since the high-frequency circuit device according to the present invention is provided with such a configuration as described above, it has the following advantageous effects.

According to the high-frequency circuit device according to the present invention, the high-frequency circuit device includes a distribution circuit for distributing a signal inputted from a signal input terminal to a plurality of first lines through a branch portion, a synthetic circuit for combining signals inputted from a plurality of second lines into one through a combined portion as an output signal and outputting it from a signal output terminal, transistors respectively placed between one ends of each individual first lines of the distribution circuit and one ends of each individual second lines of the synthetic circuit, and isolators respectively connected between the transistors and the signal input terminal and between the transistors and the signal output terminal. Such a configuration makes it hard to form an unwanted oscillation loop. In its turn, a high-reliability high-frequency circuit device can be configured.

Also, the first and second lines respectively have impedance converter circuits and the isolators are respectively connected between the transistors and the impedance converter circuits. It is thus possible to increase the gain and reduce the reflection of a signal. In its turn, a high-frequency circuit device can be configured which is reduced in loss and good in power efficiency.

Further, the transistors and the first lines, and the transistors and the second lines are respectively connected through the isolators. The impedance of each isolator on the transistor side is matched to that of each transistor. The values of impedances of the isolators on the first and second line sides

5 Furthermore, the isolators are provided at the branch
portion of the distribution circuit and the combined portion of
the synthetic circuit. The isolators placed at the branch portion
are respectively connected to the first lines different from one
another with both line ends of their output ports as signal line
10 ends. The isolators placed at the combined portion are
respectively connected to the second lines different from one
another with both line ends of their input ports as signal line
ends. Thus, the number of the isolators can be reduced and a
required substrate area can further be reduced. In its turn, a
15 small-sized and inexpensive high-frequency circuit device can be
configured.

A high-frequency circuit device comprises a distribution circuit for distributing a signal inputted from a signal input terminal to a plurality of first lines respectively having a plurality of first impedance converter circuits through a branch portion, a synthetic circuit for combining signals inputted from a plurality of second lines each having a second impedance converter circuit into one through a combined portion as an output signal and outputting it from a signal output terminal, transistors respectively placed between one ends of each individual first lines of the distribution circuit and one ends of each individual second lines of the synthetic circuit, and isolators connected either between the transistors and the branch portion of the distribution circuit or between the transistors and the combined portion of the synthetic circuit. Thus, such a configuration makes it hard to form an unwanted oscillation loop and allows a reduction in the number of the isolators, whereby a required

5

10

15